

Known Models: Browning LTD
Cobra 132, 132A, 135
Tram D60

	Both RX & TX "A"	Both RX & TX "B"	Both RX & TX "C"
Ch. 1 (26.965)	12.800	15.965	6.000
Ch. 2 (26.975)	"	"	6.010
Ch. 3 (26.985)	"	"	6.020
Ch. 4 (27.005)	"	"	6.040

	Both RX & TX "A"	Both RX & TX "B"	Both RX & TX "C"
Ch.13 (27.115)	12.800	16.115	6.000
Ch.14 (27.125)	"	"	6.010
Ch.15 (27.135)	"	"	6.020
Ch.16 (27.155)	"	"	6.040

Ch. 5 (27.015)	12.800	16.015	6.000
Ch. 6 (27.025)	"	"	6.010
Ch. 7 (27.035)	"	"	6.020
Ch. 8 (27.055)	"	"	6.040

Ch.17 (27.165)	12.800	16.165	6.000
Ch.18 (27.175)	"	"	6.010
Ch.19 (27.185)	"	"	6.020
Ch.20 (27.205)	"	"	6.040

Ch. 9 (27.065)	12.800	16.065	6.000
Ch.10 (27.075)	"	"	6.010
Ch.11 (27.085)	"	"	6.020
Ch.12 (27.105)	"	"	6.040

Ch.21 (27.215)	12.800	16.215	6.000
Ch.22 (27.225)	"	"	6.010
Ch.23 (27.255)	"	"	6.040

Additional Crystals: 7.7985 MHz USB Carrier Oscillator
7.8015 MHz AM/LSB Carrier Oscillator

Synthesis: ["A" + "B" + "C" - 7.800 MHz] = direct channel frequency.

Example: For Ch.1, [12.800 MHz + 15.965 MHz + 6.000 MHz] = 34.765 MHz; [34.765 MHz - 7.8 MHz] = 26.965 MHz. The IF is 7.800 MHz, which is offset slightly up or down for USB and LSB.

Compliments of:

CBC INTERNATIONAL · P.O. BOX 30655 · TUCSON AZ 85751 U.S.A.
TEL/FAX: 888-I-FIX-CBs (1-888-434-9227), (520) 298-7980 · Internet: www.cbcintl.com · Email: info@cbcintl.com